

Key Benefits:

- Safe - Child and shock-proof features
- Sleek in design
- Backup time of up to 5 hrs (depending on load)

APC Home-UPS HI800SQ and BI1000I

Backup power for home / business lighting applications

APC is the global leader in power protection solutions. Power cuts are common across the country and the average duration is close to 2 hours every day. APC, the global leader in power protection solutions has a range of Home-UPS' that provide high performance backup power for TV, lights and fans, ensuring there are no disruptions to the customer's day to day activities. The models are also sleek, safe and child-friendly.

Features & Benefits

- 1 Designed for harsh Indian power conditions.
- 2 Complete safety, thanks to child and shock proof features
- 3 Compact and aesthetic design
- 4 High quality power due to pure sine wave technology (BI1000I)
- 5 Promise of reliability - 2 years warranty on unit and 18 months years on battery
- 6 Reliable post-sales support
- 7 3 million happy customers in India
- 8 Voted Best UPS across multiple surveys



APC[®]
by Schneider Electric

Backup Time Chart *

Model	BI1000I	HI800SQ
Load	1000 VA	800 VA
Full Load	Up to 1 hr 45 mins (660 W)	Up to 2 hrs (500 W)
Half Load	Up to 5 hrs (330 W)	Up to 5 hrs (250 W)

* Subject to Home-UPS battery being fully charged. Backup time available with 120Ah batteries

Load Supported

	BI1000I	HI800SQ
Lights	5	5
Fans	4	3
Television	2	1

Specifications

Model	BI1000I	HI800SQ
Capacity	100 VA / 660 W	800 VA / 500 W
Output wave form	Pure Sine wave	Squarewave
Voltage on Mains	100 - 290 V	100 - 290 V
Frequency (Input)	47 - 53 Hz	47 - 53 Hz
Voltage (on Battery)	230 V	230 V
Frequency (on Battery)	50 Hz +/- 1%	50 Hz +/-1%
Transfer Time	< 20 milli seconds	< 20 milli seconds
Overload Indication	if load > 100% for 60 seconds, indications via LED & audible alarm with 3 times restart	
Charger	Constant power, 2 step charging Input voltage range 100 - 290 V	
Short circuit protection	Multiple short circuit protection provided	
Protection	Overload, short circuit, low battery Overcharge, mains low & high input voltage	

AMERICAN POWER CONVERSION (INDIA) PVT. LTD.

Toll Free Helpline 1800 4254 877
1800 4254 272

From mobile phones
(your city code) 390 222 72

Email : indiainfo@apcc.com

Visit: <http://reseller.apc.com>

APC
by Schneider Electric